Firma: Player 387 doo
Adresa: Njegoševa 16
Telefon: +387 55 209 104
Fax:
PIB: 403444110009
E-mail: porudzbine@player.ba

Marantz CD60 Black CD Plejer

Šifra: 16461
Kategorija prozivoda: CD Plejeri
Proizvođač: Marantz



Cena: 1.566,00 KM

Glatki transport diska ovog plejera ima lepu, stabilnu asistenciju u robusnoj čeličnoj konstrukciji sa duplim dnom, i aluminijumskom prednjom pločom na prednjem panelu. Sa više od 7 kilograma, ima zadovoljavajuću težinu, garant dodatne stabilnosti.

DAC opcije & pojačalo za slušalice

CD60 poseduje digitalni audio konverter referentne klase, sa rezolucijom do 24-bit/192kHz. Bilo da koristite CD čitač ili koristite USB port na prednjem panelu, za čitanje sa eksternog fleš drajva - digitalni filter pružiće vam mogućnost da reprodukciju prilagodite sopstvenom slušalačkom iskustvu. Takođe možete upotrebiti i optički ili koaksijalni digitalni izlaz, za povezivanje sa spoljnim DAC-om.

Ugrađeno HDAM®-SA2 pojačalo za slušalice poseduje tri Gain podešavanja za savršeno uklapanje sa praktično bilo kojim slušalicama.

Product highlights:

plays CDs, CD-Rs & CD-RWs plus WMA and MP3 CDs

supports FLAC, WAV, AIFF, ALAC and DSD playback from a connected USB flash drive (sold separately)

high-performance 24-bit/192kHz digital-to-analog converter
DSD 5.6MHz

selectable digital filter lets you tailor the DAC's performance to your listening preference

double-layered metal bottom plate for vibration resistance

newly optimized Marantz HDAM® (Hyper Dynamic Amplifier Module) used in analog circuitry for faster signal transfer and better transient response

high-performance HDAM-SA2 headphone amplifier with selectable low/mid/high gain settings

robust, high-speed power supply for rich, dynamic sound

frequency response: 2-20,000 Hz

signal-to-noise ratio: 118 dB

total harmonic distortion: 0.0015%

Connections:

optical and coaxial digital outputs

gold-plated stereo analog RCA output

front-panel USB input (Type A) for USB flash drives

built-in headphone amplifier with full-size (1/4") front-panel

headphone jack and volume control

IR flasher input

remote control input/output (for use with compatible Marantz receivers and amps)

General

Unit (W x H x D mm)	442 x 1 396
Net weight	7.5kg
Packaging Dimensions (W x H x D mm)	525×2
Panel Color	Availab Colors: Silver/ and Ma Black
Front (Center) Panel	Alumin

Specifications

Frequency response	USB DSD: 2Hz - 50kHz 3dB) USB PCM: 2Hz - 50kHz 1.5dB) CD: 2H - 20kH
Total Harmonic Distortion	USB DSD: 0.0006 USB PCM 24bit: 0.0005 CD: 0.0015
Signal to Noise Ratio	USB DSD: 110dB USB PCM 24bit: 118dB CD: 118dB

Dynamic Range	USB DSD: 110dB USB PCM 24bit: 118dB CD: 101dB
Line Output Level	2.2Vrm
Headphone Output Level	28mW 32 ohm
Power Consumption	38W
at Standby	0.3W

Audio Feature

HDAM	New HDAM HDAM-SA2
Power Transformer	EI
Headphone Amp	High sl rate op amp + HDA SA2
H/P Amp Gain Setting	Yes (Lo Mid / High)
Digital Filter	Filter 1 Selecta

Connectivity / Playback Capability

CD Compatibility	CD / CD-R/RW / WMA / MP3 / AAC
Data Disc Compatibility	DSD / WAV / ALAC
Fixed Analog Output (RCA)	1 (Gold Plated)
Optical input / output (Maximum Support)	0 / 1
Coaxial input / output (Maximum Support)	0 / 1

Headphone Output	1
Remote Control Bus Terminal	Yes (RC-5 I / Out) w/ Externa / Interna Select Switch
Flasher Input	Yes (U ver)
USB A	1 (Front) Mass Storage Class 5V/1A
Support format	FAT 16/32

USB-A: FLAC / WAV / AIFF / ALAC / DSD	Yes / Yes / Yes / Yes
DSD Native Playback	Yes
USB Firmware Update	Yes

Easy to use

Cene su informativnog karaktera. Prodavac ne odgovara za tačnost cena iskazanih na sajtu, zadržava pravo izmena cena. Ponudu za ostale artikle, informacije o stanju lagera i aktuelnim cenama možete dobiti na upit. Plaćanje se isključivo vrši virmanski - bezgotovinski.