

MARTIN WISMAN PMF 1200 MK2 - Aktivna mikseta - Mikseta sa snagom

Šifra: 13109

Kategorija proizvoda: Miksete sa Snagom

Proizvođač: Martin Wisman

Cena: 998,00 KM



Ultra low noise 12 channel Mic/Line Power Mixer

Features

12 Mono Input Channels with silver plated XLRs and balanced Line Inputs

Ultra low noise discrete Mic Preamps with +48V Phantom Power

Ultra-musical 3-band EQ on all channels

Peak LEDs all Mono Channels

1 Aux Send per channel for external effects

Built in digital multi effect (16DSP)

2-Track Inputs assignable to Master Mix Output

Highly accurate 10 segment Bargraph Meters

1 Stereo master output and 1 Stereo Group output

(Separate Master Mix Outputs)

Specifications

Channel MC Line: 12 MONO

Channel EQ: 3 BAND

Main Buses: 1 Stereo

Group Buses: 1 Stereo

Graphic EQ (Main): 2x7 Main

Phantom Power: +48V

Effect: 16DSP

Power Out: 350W + 350W

Dimensions: 650x530x160

Mono Inputs

Mic Input

Electronically balanced, discrete input configuration

Bandwidth

10Hz to 60kHz \pm 3dB

Distortion (THD & N)

0.01% at +4dBu, 1kHz, Bandwidth 80kHz

Mic E.I.N (22Hz - 22kHz)

-129.5 dBu, 150 Ohm source
-117.3 dBqp, 150 Ohm source
-132.0 dBu, input shorted
-122.0 dBqp, input shorted

TRIM range

+10dB to +60dB

Line Input

Electronically balanced

Bandwidth

10Hz to 60kHz \pm 3dB

Distortion (THD & N)

0.01% at +4dBu, 1kHz, Bandwidth 80kHz

Line level range	+10dBu to -40dBu
Equalization	
Hi Shelving	12kHz +/-15dB
Mid Range	2.5kHz +/-15dB
Lo Shelving	80Hz +/-15dB
Master Mix Section	
Max Output	+22dBu balanced
Aux Send Max Out	+22 dBu unbalanced
Control Room Out	+22 dBu unbalanced
Signal-To-Noise Ratio	112dB, all channels at Unity gain
Power supply	
Main voltage	~220V AC, 50Hz

Power

350W + 350W